


Delay off without supply voltage

MFT SA23S



MFT SA23S

- 5 Function, 4 time ranges
- Multivoltage:
24 ... 240 VAC/DC
- 2 Output contacts

Functions

- E** On delay
- A** Off delay without auxiliary voltage
- W2** Wiping on trailing edge voltage control (non-resetting on voltage failure)
- I1** Pulse limitation timer voltage control (non-resetting on voltage failure)
- W3** Wiping on leading and trailing edge voltage control (non-resetting on voltage failure)

Time end ranges

Adjustable 0,1 s ... 3 min.

Output relay

2 changers potential free
250 VAC / 8 A

Indicators

Green LED ON: indication of supply voltage

Connecting voltage

24 ... 240 VAC/DC, ac: -15% +10%, dc: -10% +10%
48 ... 63 Hz, 100% duration of operation, IEC class 1c

Reference data

Selectron® MFT	Article no.
MFT SA23S	41140008
(Order data see chapter 1)	



Note:


After transport the output relay maybe in any position.
The correct operation will be given after the first cycle.

Delay off without supply voltage

MFT SA23S

Technical data		
Nominal consumption		
AC		1 VA / 0.5 W
DC		0.7 VA / 0.7 W
Accuracy		
Base accuracy		± 1% of scale limit ≤ 10% for time range 1s
Repetition accuracy		1% or 100 ms
Adjustment accuracy		< 5% of scale limit
Temperature influence		≤ 0,02% / °C
Reaction time		
Recovery time		100 ms

Type key



Delay off without supply voltage

MFT SA23S

Function descriptions

E - On delay

Activation by U_s via K1. When K1 closes, the set interval t begins (green LED U illuminated).



After the interval t has elapsed, the output relay picks up and remains in the working position until K1 is opened again. Interrupting U_s during the interval t causes a reset.

A - Off delay

Activation by U_s via K1. The output relay picks up after K1 closes. If K1 is opened again, the set interval t begins (green LED U not illuminated).



After the interval t has elapsed, the output relay drops back out to its rest position. Operating K1 during the interval t causes a time reset.

I1 - Pulse limitation timer voltage control

Activation by U_s via K1. When K1 closes, the output relay picks up immediately and the set interval t begins (green LED U illuminated).



After the interval t has elapsed, the output relay drops back out to its rest position. This condition is maintained until U_s is interrupted. Interrupting U_s before the interval t has elapsed means that the output relay remains picked up until the interval t has fully elapsed.

W2 - Wiping on trailing edge voltage control

Activation by U_s via K1. The output relay remains dropped out after K1 closes. As soon as K1 is opened, the output relay picks up and the set interval t begins (green LED U not illuminated).



After the interval t has elapsed, the output relay drops out. Closing K1 before the interval t has elapsed means that the

output relay remains picked up until the interval t has fully elapsed.

W3 - Wiping on leading and trailing edge voltage control

Activation by U_s via K1. When K1 closes, the output relay picks up and the set interval t begins (green LED U illuminated).



After the interval t has elapsed, the output relay drops out. As soon as K1 is opened, the output relay picks up and the set interval t begins (green LED U not illuminated).

After the interval t has elapsed, the output relay drops out. Interrupting or re-applying U_s before the interval t has elapsed means that the output relay remains picked up until the interval t has fully elapsed.


Delay off without supply voltage

MFT SA23S

Connection


MFT SA23S

24 ... 240 VAC/DC



Load limit curve

MFT SA23S



Dimensions

